SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT WE, Kaoru Usui, a citizen of Japan residing at Kawasaki, Japan, Yoshio Shimano, a citizen of Japan residing at Kawasaki, Japan, Hiroshi Iizuka, a citizen of Japan residing at Kawasaki, Japan and Hiroyuki Itou, a citizen of Japan residing at Sapporo, Japan have invented certain new and useful improvements in

LIGHT AMPLIFYING APPARATUS FOR WAVELENGTH DIVISION
MULTIPLEXING CAPABLE FOR DETERMINING CHANGE IN NUMBER
OF MULTIPLEXED WAVELENGTH SIGNALS

of which the following is a specification:-

TITLE OF THE INVENTION

LIGHT AMPLIFYING APPARATUS FOR WAVELENGTH
DIVISION MULTIPLEXING CAPABLE FOR DETERMINING CHANGE
IN NUMBER OF MULTIPLEXED WAVELENGTH SIGNALS

5

10

15

20

25

30

35

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to a photo (light) amplifying apparatus, and more particularly, to a photo amplifying apparatus for amplifying wavelength division multiplexing (WDM) signals that includes a measuring unit that measures the power of a specific wavelength, a measuring unit that measures the total power of all wavelengths, and a controlling unit that controls the output power of the photo amplifying apparatus.

2. Description of the Related Art
Wavelength division multiplexing (WDM) is
a pervading broad band technology in which a
plurality of photo signals of different wavelengths
is transmitted via a single optical transmission
path.

The wavelength division multiplexing technology is applied to multi-channel optical communications of various distances. In practice, wavelength division multiplexing communication systems are required to flexibly support optical communications of various wavelengths and distances.

In general, a WDM photo amplifying apparatus of the WDM communication system amplifies photo signals so that the output power of output photo signals of each wavelength becomes equal. To achieve this object, the WDM photo amplifying apparatus controls excitation light sources and optical attenuators provided therein based on information about the power of photo signals monitored at various stages in the optical path and

information for setting gain, the number of wavelengths, and output power, for example, received from an exterior resource.

FIG. 1 is a schematic diagram showing a conventional photo amplifying apparatus. The photo amplifying apparatus shown in FIG. 1 includes photo amplifying units 1, 2, a variable optical attenuator 6, a control unit 7, optical splitters 12-15, and photo diodes (optical monitors) 32-35.

5

The photo amplifying units 1, 2 further include Erbium-doped Fiber Amplifiers (EDFA) 3, 4, laser diodes (excitation light sources) 21, 22, and wavelength mixers 41, 42, respectively. The photo amplifying unit 1 further includes a gain equalizer 5.

The EDFAs 3, 4 are excited by the laser diodes 21, 22, respectively.

FIG. 2 is a graph showing the distribution of power (dBm) over wavelength (nm) of wavelength division multiplexing signals. As shown in FIG. 2, X_{in} denotes the power of photo signals of each wavelength $\lambda 1-\lambda n$. The WDM signal having the power distribution shown in FIG. 2 is input to the photo amplifying apparatus via a input terminal IN. A fraction of the input photo signals is split from the main signal by the photo splitter (photo coupler) 12, and converted into an electric signal by the photo diode 32.

FIG. 3 is a schematic diagram showing the power of the photo signals monitored by the photo diode 32. The output of the photo diode 32 depends only on the total power (= $X_{in} + 10 \times log(n)$) of photo signals over all wavelengths $\lambda 1 - \lambda n$. Likewise, the outputs of the photo diodes 33-35 depend only on the total power of photo signals over all wavelengths $\lambda 1 - \lambda n$ incoming to the photo splitters 13-15, respectively.

The control unit 7 controls the power of each stage based on the total power of the photo signals over all wavelengths $\lambda 1-\lambda n$ monitored by the photo diodes 32-35. As a result, the photo amplifying apparatus shown in FIG. 1 outputs the objective output photo signals via an output terminal OUT.

FIG. 4 is a schematic diagram for explaining the automatic level control (ALC)

10 performed by the control unit 7. The control unit 7 of the photo amplifying apparatus shown in FIG. 1 automatically controls the optical level of each stage as follows:

- (1) Controlling the laser diode 15 (excitation light source) 21 so that the difference between the output $P_{\text{PD}33}$ of the photo diode 33 and the output $P_{\text{PD}32}$ of the photo diode 32 becomes constant.
 - $P_{PD33} P_{PD32} = A \text{ (constant)}. \dots (1)$
- (2) Controlling the laser diode (excitation light source) 22 so that the difference between the output $P_{\text{PD}35}$ of the photo diode 35 and the output $P_{\text{PD}34}$ of the photo diode 34 becomes constant.
- $P_{PD35} P_{PD34} = B \text{ (constant)}. \dots (2)$ In the case that the photo amplifying unit 1 (or 2) cannot achieve a predetermined gain A (or B), the control unit 7 raises the gain of the photo amplifying unit 2 (or 1) so as to make A+B constant.
- 30 (3) Controlling the variable attenuator 6 so that the output power from the output terminal OUT reaches the objective output level.

As a result of the above automatic gain control, an output of which level is determined based on the number of wavelengths is obtained via the output terminal OUT.

35

FIGs. 5A and 5B are schematic diagrams for

explaining a problem that occurs in the case wherein the control unit 7 fails to control the output from the output terminal OUT at the level determined based on the number of wavelengths.

FIG. 5A illustrates the case wherein two wavelengths are used. The output powers of both wavelengths $\lambda 1$, $\lambda 2$ are assumed to be equal to the same value $X_{\rm in}$. Under such a condition, the case in which the light source of the wavelength $\lambda 2$ accidentally malfunctions is examined below.

5

10

15

20

25

30

35

Since the number of wavelengths to be amplified by the photo amplifying apparatus is reduced from two wavelengths to one wavelength, the output level of the photo amplifying apparatus is expected to be halved. However, if the control unit 7 is not informed that the number of input wavelengths is reduced to one, the control unit 7 compensates for the reduction in power level caused by the disappearance of wavelength $\lambda 2$ by increasing the output level of $\lambda 1$. Consequently, the control unit 7 cannot keep the output level per wavelength constant.

To solve this problem, in a large-capacity long-distance WDM communication system, an upper-rank photo transmitting apparatus informs the photo amplifying apparatus of a lower-rank photo transmitting apparatus of information such as the number of wavelengths and the output level of each wavelength to configure the photo amplifying apparatus of the lower rank photo transmitting apparatus.

The control unit 7 of the photo amplifying apparatus of the lower-rank photo transmitting apparatus controls the output based on the information (configuration information) received from the upper-rank photo transmitting apparatus so that the output power of the photo amplifying

apparatus is kept at the level corresponding to the number of wavelengths.

Since the properties of optical parts built in conventional photo amplifying apparatuses are dispersed, the conventional photo amplifying apparatuses are adjusted one by one in an adjustment process of production so that the gradient of gain over wavelength becomes flat and the gains satisfy the following equations:

 $P_{PD33} - P_{PD32} = A (dB) (constant), and (1)$

10

15

20

25

30

35

 $P_{PD35} - P_{PD34} = B \text{ (dB) (constant)}.$ (2)

Japanese Patent Laid-open Application No. 2000-312046 discloses a technique with which difference between gains of a photo amplifying apparatus determined by various input wavelengths caused by change in optical fiber loss can be eliminated. According to this application, a controlling unit built into the photo amplifying apparatus controls the operation of the photo amplifying apparatus based on the intensity of received reference light.

Japanese Patent Laid-open Application No. 2000-196169 discloses a technique for a photo amplifying apparatus of a WDM communication system that multiplexes and transmits a plurality of photo signals with which the degradation of nonlinear property and signal-to-noise ratio due to change in the number of channels is eliminated. According to this application, a photo amplifying apparatus is provided with the following: a first portion including an optical fiber with rare earth element doped, an excitation laser diode, and an automatic optical gain control circuit; a second portion including an optical attenuator and an automatic level control circuit; and a monitor signal processing circuit. Before a change in the number of channels, the photo amplifying apparatus outputs

amplifying a WDM signal of which level is determined by the number of channels. When the photo amplifying apparatus is informed of the change in the number of channels, the photo amplifying apparatus temporarily fixes the transmissivity of the optical attenuator, and keeps its gain constant so as to output a photo signal of which level corresponds to the number of channels. After the change in the number of channels, the photo amplifying apparatus resumes controlling the transmissivity of the optical attenuator and its gain.

10

15

20

25

30

35

In the case in which a signal of a certain wavelength unexpectedly vanishes due to the malfunction of a light source, for example, the upper-rank photo transmission apparatus determines that the number of wavelengths has changed. After the determination, the upper-rank photo transmission apparatus informs the photo amplifying apparatus of a lower-rank photo transmission apparatus receiving configuration information (the number of wavelengths and the output levels, for example) from the upperrank photo transmission apparatus, about the change in the number of wavelengths. Accordingly, the photo amplifying apparatus receives the information indicating that the number of wavelengths has changed in a delay (from hundreds of msec to several sec) after the number of wavelengths actually changes.

A conventional photo amplifying apparatus absorbs the delay to the extent from hundreds of msec to several sec in the following manner.

An optical attenuator with a dead time from hundreds of msec to several sec may be used; the optical attenuator operates with the delay from hundreds of msec to several sec. Even if the photo amplifying apparatus receives the information indicating that the number of wavelengths has

changed, during the delay (from hundreds of msec to several sec) after the number of wavelengths actually changes, the optical attenuator does not react. Accordingly, the photo amplifying apparatus is not affected by the delay time.

5

20

25

30

Alternatively, monitoring circuits sampling signal levels at each stage may be required to retain their sampled values for a retention time of about several seconds. Since an optical attenuator is controlled based on the sampled signal levels monitored by the monitoring circuits, the optical attenuator is controlled after the retention time of several seconds. Accordingly, the photo amplifying apparatus can avoid being affected by the delay in receiving the information.

However, the time required for the information of the number of wavelengths to be transmitted from the upper-rank photo transmission apparatus to the photo amplifying apparatus depends on the performance of the upper-rank photo transmission apparatus for determining the number of wavelengths, and consequently, differs one after another. There remains a problem in that the above dead time and/or holding time needs to be optimized for each upper rank photo transmission apparatus.

Because the total gain of a photo amplifying apparatus is desired to be indifferent for various wavelengths, the gain of the photo amplifying unit of the photo amplifying apparatus needs to be adjusted to compensate for the difference in optical efficiency of the remaining portion of the photo amplifying apparatus other than the photo amplifying unit.

Conventionally, the gain of the photo
35 amplifying unit of each WDM photo amplifying
apparatus is individually adjusted in the production
process based on a test condition (for example the

maximum number of wavelengths). Accordingly, if the WDM photo amplifying apparatus is used in practice under a different condition (for example the number of wavelengths) from the test condition defining the maximum number of wavelengths, for example, the desired flatness of the total gain of the WDM photo amplifying apparatus may not be achievable.

For example, as shown in FIG. 6, even though the photo amplifying apparatus is adjusted in its production process based on the maximum number of wavelengths (ten, for example), the photo amplifying apparatus is often used with the number of wavelengths (seven, for example) being less than the maximum number. In this case, the gain of the photo amplifying apparatus may exhibit a gradient as shown in FIG. 7.

The invention taught in Japanese Patent Laid-open Application No. 2000-312046 still inherits a problem that the wavelength of the reference light needs to be different from the wavelength of the main signals. Another problem of the invention is that the number of wavelengths cannot be identified.

According to the invention taught in Japanese Patent Laid-open Application No. 2000-196169, when the wavelength number is changed, the transmissivity, for example, of the optical attenuator is temporarily fixed, and then, after the wavelength number is changed, the control of the optical attenuator is resumed. This invention also inherits the above problems.

SUMMARY OF THE INVENTION

10

15

20

25

30

35

Accordingly, it is a general object of the present invention to provide a novel and useful photo amplifying apparatus in which one or more of the problems described above are eliminated.

Another and more specific object of the

present invention is to provide a photo amplifying apparatus that detects the change in wavelength number and the gain gradient of photo signals based on the photo signals, and controls the output level.

To achieve one or more of the above objects, a photo amplifying apparatus for amplifying wavelength division multiplexing signals, according to an aspect of the present invention, includes:

5

10

15

30

35

a specific wavelength measuring unit that measures the light power of photo signals of a specific wavelength at a measuring point;

a total power measuring unit that measures the light power of the photo signals of all wavelengths at the measuring point; and

an output control unit that controls the output of the photo amplifying apparatus based on the light power measured by the partial wavelength measuring unit and the light power measured by the total power measuring unit.

20 The photo amplifying apparatus measures both the light power of a specific wavelength and the light power of all wavelengths at the measuring point. Accordingly, the photo amplifying apparatus can determine a change in the number of multiplexed wavelengths and in the gain gradient of the photo signal based on the measured light power, and can properly control its output level.

According to another aspect of the present invention, the photo amplifying apparatus is further characterized in that the specific wavelength measuring unit further includes a variable-wavelength optical filter.

Even if a specific wavelength (signal) stops due to a malfunction, for example, the photo amplifying apparatus provided with the variable-wavelength optical filter can switch to an alternative wavelength and continue monitoring the

light power of the alternative wavelength.

Accordingly, the output control unit can continuously control the photo amplifying apparatus.

Other objects, features, and advantages of the present invention will be more apparent from the following detailed description when read in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

10 FIG. 1 is a schematic diagram showing a conventional photo amplifying apparatus;

FIG. 2 is a graph for explaining photo signals input to a photo amplifying apparatus;

FIG. 3 is a graph for explaining the total

15 power of photo signals monitored by a photo diode;

FIG. 4 is a graph for explaining the amplification and attenuation of photo signals by a photo amplifying apparatus;

FIGs. 5A and 5B are graphs for explaining 20 a problem caused by the reduction in number of wavelengths;

FIG. 6 is a graph for explaining the flatness of gain over the maximum number of wavelengths;

25 FIG. 7 is a graph for explaining the gradient of gain over seven wavelengths;

FIG. 8 is a schematic diagram showing a photo amplifying apparatus according to the first embodiment of the present invention;

FIG. 9 is a flow chart for obtaining the number of wavelengths;

FIG. 10 is a schematic diagram showing a photo amplifying apparatus according to the second embodiment of the present invention;

FIG. 11 is a flow chart for making gains flat (constant);

FIG. 12 is a circuit diagram for

explaining processing for flattening gains;

FIG. 13 is a schematic diagram showing a photo amplifying apparatus according to the third embodiment of the present invention;

FIG. 14 is a schematic diagram showing a photo amplifying apparatus according to the fourth embodiment of the present invention;

FIG. 15 is a schematic diagram showing a photo amplifying apparatus according to the fifth embodiment of the present invention; and

FIG. 16 is a schematic diagram showing a photo amplifying apparatus according to the sixth embodiment of the present invention.

15 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention are described below with reference to the drawings.

[FIRST EMBODIMENT]

5

10

25

30

20 FIG. 8 is a schematic diagram showing a photo amplifying apparatus according to the first embodiment of the present invention.

The photo amplifying apparatus shown in FIG. 8 includes the following: photo amplifying units 1, 2, a variable optical attenuator 6, a control unit 7, optical splitters 11-15, photo diodes 31-35, and a fixed optical filter 51.

The fixed optical filter 51 transmits photo signals of a specific wavelength. The photo amplifying unit 1 further includes a laser diode 21 (excitation light source), a wavelength mixer 41, EDFA 3, and gain equalizer 5. The photo amplifying unit 2 further includes a laser diode 22 (excitation light source), a wavelength mixer 42, and EDFA 4.

35 WDM photo signals (wavelengths: $\lambda 1 - \lambda n$, intensity X_{in}) are provided to a photo signal input terminal IN. The input photo signal is amplified by

the photo amplifying unit 1. The amplified photo signal is attenuated down to a predetermined signal level by the variable optical attenuator 6. The attenuated photo signal is amplified up to a predetermined signal level by the photo amplifying unit 2. Then the amplified photo signal is output from the photo signal output terminal OUT.

The photo diode 31 detects the signal level (P_{PD31}) of the photo signal of the specific wavelength transmitting through the fixed optical filter 51. The photo diode 32 detects the total power P_{PD32} of photo signals (wavelengths: $\lambda 1 - \lambda n$) before being amplified by the photo amplifying unit 1. Likewise, the photo diode 33 detects the total power P_{PD33} of photo signals (wavelengths: $\lambda 1 - \lambda n$) after being amplified by the photo amplifying unit 1.

10

15

20

25

30

35

The photo diode 34 detects the total power P_{PD34} of photo signals (wavelengths: $\lambda 1 - \lambda n$) before being amplified by the photo amplifying unit 2. The photo diode 35 detects the total power P_{PD35} of photo signals (wavelengths: $\lambda 1 - \lambda n$) after being amplified by the photo amplifying unit 2.

(1) The control unit 7 of the photo amplifying apparatus controls the laser diode (excitation light source) 21 so that the difference between the output $P_{\text{PD}33}$ of the photo diode 33 and the output $P_{\text{PD}32}$ of the photo diode 32 becomes constant.

 $P_{PD33}-P_{PD32}=D$ (dB) (constant) (3)

(2) The control unit 7 of the photo amplifying apparatus controls the laser diode (excitation light source) 22 so that the difference between the output P_{PD35} of the photo diode 35 and the output P_{PD34} of the photo diode 34 becomes constant.

 $P_{PD35}-P_{PD34}=E$ (dB) (constant) (4) (3) If the gain of either the photo

amplifying unit 1 or the photo amplifying unit 2 cannot achieve the predetermined gains D or E, the control unit 7 of the photo amplifying apparatus raises the gain of the other photo amplifying unit 2 or the photo amplifying unit 1 so that

D+E= constant (5)

5

10

15

20

25

30

(4) The control unit 7 of the photo amplifying apparatus controls the variable optical attenuator 6 so that the output power P_{PD35} from the output terminal OUT is tuned at a target output level.

Assuming the light intensity input to the photo signal input terminal IN is "a" (dBm/ch), and the light intensity output from the photo signal output terminal OUT is "b" (dBm/ch), the light intensities P_{PD31} , P_{PD32} , and P_{PD35} monitored by the photo diodes 31, 32, and 35, respectively, are:

$$P_{PD31} = a (dBm/ch) \dots (6)$$
 $P_{PD32} = a + 10 \times log(n) (dBm)$
[total power] \dots (7)
 $P_{PD35} = b + 10 \times log(n) (dBm)$

[total power]

If the loss of the transmission path connected to the photo signal input terminal IN changes +/-x (dB), the light intensities P_{PD31} and P_{PD32} monitored by the photo diodes 31 and 32, respectively, becomes:

$$P_{PD31} = a \pm x (dBm/ch)$$
 (9)
 $P_{PD32} = a + 10 \times log(n) \pm x (dBm)$
.... (10)

Assuming the change in the monitored photo intensities P_{PD31} and P_{PD32} being $\Delta x1$ and $\Delta x2$, respectively, the equations (6), (7), (9), and (10) lead to the following relations:

35
$$\Delta \mathbf{x} \mathbf{1} = \pm \mathbf{x} \quad \dots \quad (11)$$
$$\Delta \mathbf{x} \mathbf{2} = \pm \mathbf{x} \quad \dots \quad (12)$$

Accordingly, $\Delta x1$ and $\Delta x2$ are equal.

On the other hand, if the wavelength number changes from "n" to "n \pm m", the light intensities $P_{\text{PD}31}$ and $P_{\text{PD}32}$ monitored by the photo diode 31 and the photo diode 32, respectively, are obtained as follows:

5

25

30

 $P_{PD31} = a (dBm/ch)$ (13) $P_{PD32} = a + 10 \times log(n \pm m)$ [total power] (14)

As is understandable from the above equations, whereas the light intensity P_{PD31} monitored by the photo diode 31 does not change $(\Delta x1=0)$, the change $\Delta x2$ in the light intensity P_{PD32} is:

 $\Delta x^2 = 10 \times \log[(n \pm m)/n] \dots$ (15)

15 Accordingly, when detecting change in the input signal level, one can determine whether the change is caused by either the loss of the transmission path or the change in wavelength number by comparing the change $\Delta x1$ and $\Delta x2$ in the monitored light intensities P_{PD31} and P_{PD32} .

If the light intensity P_{PD31} monitored by the photo diode 31 and the light intensity P_{PD32} monitored by the photo diode 32 change in the same quantity, one can determine that the change in the input signal level is caused by the loss of the transmission path. If the monitored light intensity P_{PD31} monitored by the photo diode 31 does not change, but the monitored light intensity P_{PD32} monitored by the photo diode 32 does change, one can determine that the change in the input signal level is caused by the change in wavelength number.

Since "n" is known, the change in wavelength number "m" is obtained based on the equation (15) as follows:

35 $m = \pm n \times (10^{\Delta_{\rm X2/10}} - 1) \ldots (16)$ Accordingly, the photo amplifying apparatus can identify the current number of

wavelengths as soon as the input signal changes without waiting for configuration information about the number of wavelengths to be transmitted from the upper rank monitoring apparatus of the photo amplifying apparatus. Consequently, it is not necessary to set a dead time or a time lag of the photo amplifying apparatus, or optimize the dead time or the time lag depending on the upper rank photo transmission apparatus.

Additionally, since the photo amplifying apparatus can identify the number of wavelengths, the photo amplifying apparatus can control the optical attenuator 6 so that the output photo signal achieves a target:

without waiting for the configuration information transmitted from the upper rank observing apparatus of the photo amplifying apparatus.

FIG. 9 is a flow chart showing the calculation of the number of wavelengths "m" by the control unit 7 of the photo amplifying apparatus shown in FIG. 8.

The light intensity is monitored by the photo diodes 31 and 32 (step S2). Then, the changes $\Delta x1$ and $\Delta x2$ in the light intensities monitored by the photo diodes 31 and 32, respectively, are calculated (step S3).

 $\Delta x1$ and $\Delta x2$ are compared (step S4). If $\Delta x1$ 30 = $\Delta x2$, which means that the change in the input signal level is caused by a loss of the transmission path, the process returns to step S2. If $\Delta x1 \neq \Delta x2$, the increased or decreased number of wavelengths is obtained based on the equation (16) (step S5).

As described above, since the photo amplifying apparatus shown in FIG. 8 can alone identify the number of wavelengths, the photo

amplifying apparatus does not need to be provided with dead time or retention time of hundreds msec for controlling the photo output signal to be constant. The photo amplifying apparatus consequently can control the photo output signal at high speed.

5

10

30

35

The photo amplifying apparatus detects the change in the number of wavelengths as soon as the change occurs, and controls the photo output signal based on the detected change in the number of wavelengths. Accordingly, the control by the photo amplifying apparatus becomes stable.

[SECOND EMBODIMENT]

The second embodiment of the present

invention is described with reference to FIG. 10. A

photo amplifying apparatus of FIG. 10 includes the
following: photo amplifying units 1, 2, a variable
optical attenuator 6, a control unit 7, optical
splitters 12-16, photo diodes 32-36, and a fixed

optical filter 52. The photo amplifying unit 1
further includes a laser diode (excitation light
source) 21, a wavelength mixer 41, an EDFA 3, and a
gain equalizer 5. The photo amplifying unit 2
further includes a laser diode (excitation light
source) 22, a wavelength mixer 42, and an EDFA 4.

Elements that are identical to those of the photo amplifying apparatus shown in FIG. 8 are referred to by the same numerals, and their description is omitted. The photo amplifying apparatus shown in FIG. 10 is basically the same as the photo amplifying apparatus shown in FIG. 8 except for the optical splitter 11, the fixed optical filter 51, and the photo diode 31 that are removed, and the optical splitter 16, the fixed optical filter 52, and the photo diode 36 that are added. The fixed optical filter 52 transmits a photo signal of specific wavelength.

WDM photo signals (wavelengths: $\lambda 1 - \lambda n$, intensity X_{in}) are provided to a photo signal input terminal IN. The input photo signal is amplified by the photo amplifying unit 1. The amplified photo signal is attenuated down to a predetermined signal level by the variable optical attenuator 6. The attenuated photo signal is amplified up to a predetermined signal level by the photo amplifying unit 2. Then the amplified photo signal is output from the photo signal output terminal OUT.

5

10

35

The photo diode 32 detects the total power P_{PD32} of photo signals (wavelengths: $\lambda 1 - \lambda n$) before being amplified by the photo amplifying unit 1. Likewise, the photo diode 33 detects the total power P_{PD33} of photo signals (wavelengths: $\lambda 1 - \lambda n$) after 15 being amplified by the photo amplifying unit 1. The photo diode 34 detects the total power P_{PD34} of photo signals (wavelengths: $\lambda 1 - \lambda n$). The photo diode 35 detects the total power $P_{\mbox{\scriptsize PD35}}$ of the photo signals (wavelengths: $\lambda 1 - \lambda n$) after being amplified by the 20 photo amplifying unit 2. The photo diode 36 detects the signal level (P_{PD36}) of the photo signal of the specific wavelength transmitting through the fixed optical filter 52.

25 (1) The control unit 7 of the photo amplifying apparatus controls the laser diode (excitation light source) 21 so that the difference between the output $P_{\text{PD}33}$ of the photo diode 33 and the output $P_{\text{PD}32}$ of the photo diode 32 becomes 30 constant.

 $P_{PD33} - P_{PD32} = D$ (dB) (constant) (3) (2) The control unit 7 of the photo

amplifying apparatus controls the laser diode (excitation light source) 22 so that the difference between the output P_{PD35} of the photo diode 35 and the output P_{PD34} of the photo diode 34 becomes constant.

 $P_{PD35} - P_{PD34} = E \text{ (dB) (constant)} \dots (4)$

(3) If either the photo amplifying unit 1 or the photo amplifying unit 2 cannot achieve the respective predetermined gains D or E, the control unit 7 of the photo amplifying apparatus raises the gain of the other photo amplifying unit 2 or the photo amplifying unit 1 so that

 $D+E = constant \dots (5)$

(4) The control unit 7 of the photo amplifying apparatus controls the variable optical attenuator 6 so that the output power P_{PD35} from the output terminal OUT is tuned to a target output level.

The control unit 7 controls the laser diodes 21 and 22 that are excitation light sources of the EDFA 3 and 4, respectively, and consequently, controls the gains of the photo amplifying units 1 and 2 so as to make their gains flat enough.

The following equation needs to be

20 satisfied:

15

25

30

35

[(P_{PD35} -ASE)/n] / P_{PD36} = constant(18)

where "n" is the number of wavelengths amplified by the photo amplifying apparatus, and ASE is noise power caused by accumulated spontaneous emission, for example.

 $(P_{PD35}-ASE)$ is the power of signal component, and $(P_{PD35}-ASE)/n$ is the power of signal component per a wavelength. The equation (18) means that the ratio between the power of signal component per a wavelength and P_{PD36} is constant. P_{PD36} is the power of an arbitrarily selected wavelength. The constant ratio between the power of the arbitrarily selected wavelength and the average power over "n" wavelengths means that the gain of the photo amplifying apparatus is flat. ASE is determined based on a different experiment.

If the equation (18) is not satisfied, the gain is not flat. Accordingly, the control unit 7 controls the laser diodes 21 and 22 that are excitation light sources so that the ratio between $(P_{PD35}-ASE)/n$ and the level P_{PD36} of the photo signal transmitting through the fixed optical filter 52 achieves a predetermined value.

5

10

15

20

30

35

The control unit 7 controls the variable optical attenuator 6 so that the power of photo signal per wavelength $(P_{PD35}-ASE)/n$ is kept at a predetermined value in order to compensate the power per wavelength.

FIG. 11 is a flow chart for explaining processing by the control unit 7 of the photo amplifying apparatus for making gain thereof flat.

FIG. 12 is a block diagram for explaining processing by the control unit 7 of the photo amplifying apparatus for making gain thereof flat.

The processing by the control unit 7 is described below with reference to FIGs. 11 and 12.

As shown in FIG. 12, the photo signals are received and converted into current signals by the photo diodes 32-34, 35, and 36, and are converted into voltage signals by resistors R2-R4, R5, and R6.

25 The voltage signals are amplified by amps 2-4, 5, 6, and further converted into digital signals by analog-digital converters ADC2-4, 5, and 6. Then, the digital signals are input to the control unit 7.

The control unit 7 processes the input digital signals as follows (initial operation):

(1) Detecting the signal level of outputs from AMP4, 5, and 6 (step S12).

(2) Driving the laser diode 22 that is the excitation light source of the photo amplifying unit 2 so that the ratio between electric signals of Amp 4 and 5 becomes a predetermined value to control the gain (step S13, S14).

- (3) Controlling the variable optical attenuator 6 so that the level of the electric signal of Amp 6 becomes a predetermined value (steps S15, S16).
- After the above processing, the control unit 7 performs the following to compensate the gain gradient and the output per wavelength:
 - $\,$ (4) Detecting the electric signal levels of Amp 5 and Amp 6 (step S17).
- 10 (5) Controlling the variable optical attenuator 6 so that the electric signal level of Amp 6 becomes a set value (steps S19, S20).
- (6) Controlling the laser diodes 21 and 22 that are the excitation light sources of the photo amplifying units 1 and 2, respectively, so that the equation (18) is satisfied (steps S21, S22).

If the control unit 7 receives an instruction to stop processing or detects that the input signal stops, the control unit 7 exits the processing (steps S18, S23).
[THIRD EMBODIMENT]

20

FIG. 13 is a schematic diagram showing a photo amplifying apparatus according to the third embodiment of the present invention.

25 Elements that are identical to those of the photo amplifying apparatus shown in FIG. 8 are referred to by the same reference numerals, and their description is omitted.

The photo amplifying apparatus shown in

FIG. 13 is the same as the photo amplifying apparatus shown in FIG. 8 except that the fixed optical filter 51 that transmits photo signals of a specific wavelength is replaced with a variable optical filter 61 that transmits photo signals of a specific wavelength, and a drive circuit 71 that controls the variable optical filter 61. Any wavelength can be selected with these new components.

```
The operation of the photo amplifying identical fig.

The operation 13 is apparatus shown in FIG.

apparatus shown amplifying apparatus shown in amplifying apparatus the photo amplifying to the photo amplifying the photo am
                   apparatus shown in amplifying apparatus apparatus of the photo of the nhoto amplifying advantage of the advantage of the advantage of the shown in the nhoto amount of the nhoto amount of the shown in the nhoto amount of the nh
                                      that of the photo of the embodiment is that. If the that of the advantage third embodiment is that according to the according
                                                            8. The advantage third embodiment is wavelength detected the specific wavelength of the specific wavelength according to the the specific wavelength according to the specific wavelength the specific
                                                                            according to the the specific wavelength of the the specific wavelength of the the specific wavelength to a malfunction photo signal of 31 stone due to a malfunction
                                                                                                  Photo signal of the specific wavelength detected by the photo the control unit 7 causes the variable the photo the photo the causes the control unit 7 causes the causes the control unit 7 causes the control unit 7 causes the causes the control unit 7 causes the cause the c
                                                                                                                         the photo the control to switch to another wavelend the example, example, optical
                                                                                                                                            example, the control unit 7 causes the wavelength of the control unit 7 causes ther wavelength to another wavelength to switch to another signal of the optical filter monitoring the optical continue monitoring the continue
                                                                                                                                                                  optical filter for the monitoring the case of the monitoring the case of the and continue monitoring the case of the other wavelength.
                                                                                                                                                                                     and continue monitoring the photo of the photo and continue monitoring the case of the first other wavelength. In the according to the annarative according to the photo signal of the photo signal of the photo of the ph
                                                                                                                                                                                                           other wavelength. In the case of the photo the first other wavelength. In the case of the first other wavelength. In the case of the first of the case of the first of the case of the first of the first of the case of the first of the first of the case of the first of the first of the case of the first of the first of the case of the first of
                                                                                                                                                                                                                               amplifying apparatus if the photo the nhoto diode embodiment, wavelength detected by the photo the nhoto diode
                                                                                                                                                                                                                                                  embodiment, however, detected by the photo amolifving unit 7 of the specific wavelength unit 7 of the specific the control
                                                                                                                                                                                                                                                                        specific wavelength detected by the photo amplifying unit 7 of the photo amplifying the control unit 8 fails to properly control stops, the shown in FTG. Refails to properly shows apparatus
                                                                                                                                                                                                                                                                                           the control unit 7 of the photo amplifying control unit 7 of the photo properly control to properly control the shown in FIG. stops, the shown amplifying apparatus.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          MBODIMEN'I a schematic diagram the fourth
                                                                                                                                                                                                                                                                                                                                                                        FIG. 14 is a schematic diagram the fourth apparatus according to the fourth photo amplifying apparatus invention
                                                                                                                                                                                                                                                                                                                 apparatus.

apparatus.

the photo amplifying apparatus.
                                                                                               10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          or the present invention. apparatus shown in the photo amplifying apparatus and i fring the photo amplifying the p
                                                                                                                                                                                                                                                                                                                                                                                                                                                              FIG. 14 is shown transmits a specific wavelength apparatus that that apparatus that
                                                                                                                                                                                                                                                                                                                                                                                                                                       The photo amplifying apparatus snown a maplifying apparatus amplifying apparatus amplifying apparatus snown amplifying apparatus amplifying apparatus snown amplifying apparatus amplifying apparatus snown amplifying amplifying apparatus snown amplifying amplifying apparatus snown amplifying amplifyi
                                                                                                                                                                                                                                                                                                                                                                                                       embodiment mr apparatus according
                                                                                                                                                                                                                                                                                                                                              TEOURTH EMBODIMENT!
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 apparatus that transmits a specific wavelength is transmits ontical filter 62 that transmits replaced with a variable of the replaced with a replaced with the fixed optics as specific wavelength is a specific wavelength is a specific wavelength is a specific wavelength is a specific with a variable ontical filter filter filter with a variable ontical filter with a variable ontical filter filter with a variable ontical filter with a variable ontical filter with a variable ontical filter filter with a variable ontical filter filter with a variable ontical filter fi
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    filter 52 that transmits a specific wavelength is a specific wavelength at transmits a specific wavelength arive cire filter filter for the variable wavelength and a drive cire replaced with a variable wavelength and a drive cire replaced with a variable wavelength and a transmite a variable wavelength and a transmite a variable wavelength and a transmite a variable wavelength and a drive cire transmite a variable wavelength and a variable wavelength and a variable wavelength and a drive cire transmite a variable wavelength and a 
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          replaced with a variable wavelength, optical filter 62 is transmits a variable the variable optical tales a variable the variable transmits controlling the variable transmits and controlling the variable transmits are controlling to the variable transmits and controlling the variable transmits are controlling to the variable transmits and controlling the variable transmits are controlling to the variable transmits and controlling the variable transmits are controlling to the variable transmits and controlling transmits are controlling transmits.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          transmits a variable wavelength, optical signal of the transmits a variable wavelength the photo signal of the added.

Accordingly, and a drive circuit the photo signal of the photo sign
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                The controlling the variable optical filter of the photo signal of
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   added. Accordingly, even if the photo the example, the example. added. Accordingly, detected for example. specific wavelength to a malfunction.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             stops due to a malfunction, can select an alternative for example, the mnoto signal filter to monitor the nhoto signal variable optical and continue to monitor the nature variable and continue to monitor the nature variable wavelength and continue to monitor wavelength and continue to
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             specific wavelength detected by the photo the stops due to a malfunction, can ealert an alter stops due notical filter for ealert and stops are notical filter for ealert and stops are notical filter for ealert and stops due to a malfunction.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                variable optical filter to monitor the photo signal wavelength and continue wavelength and tive wavelength and the monitor the photo signal
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            ternative wavelength, apparatus according

The photo amplifying apparatus according
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                The photo amplifying apparatus according to the fourth amplifying apparatus according to the photo amplifying apparatus according to the fourth amplifying apparatus according to the fourth amplifying apparatus according to the same manner to the fourth amplifying apparatus according to the same manner to the fourth amplifying apparatus according to the fourth amplifying the fourth amplifying the fourth amplifying the fourth
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   to the photo amplifying apparatus according to the as the photo
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         wave the alternative wavelength.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      35
```

second embodiment except that, even if the photo signal of the specific wavelength stops, the control unit 7 causes the filter drive circuit 72 to switch the stopped wavelength to another wavelength and continues to properly control.

[FIFTH EMBODIMENT]

5

15

FIG. 15 is a schematic diagram showing a photo amplifying apparatus according to the fifth embodiment of the present invention.

The fifth embodiment is the combination of the first embodiment and the second embodiment.

Compared with the photo amplifying apparatuses shown in FIGs. 8 and 10, the photo amplifying apparatus shown in FIG. 15 is different in that it is provided with both fixed optical filters 51 and 52 and both photo diodes 31 and 36.

As described with reference to FIG. 15, since the photo amplifying apparatus is provided with the fixed optical filter 51 and the photo diode 31, the photo amplifying apparatus can determine the number of wavelengths as soon as the number of wavelengths changes. Using the determined number of wavelengths, the photo amplifying apparatus can make the gain thereof flat.

25 [SIXTH EMBODIMENT]

FIG. 16 is a schematic diagram showing a photo amplifying apparatus according to the sixth embodiment.

The sixth embodiment is the combination of the third embodiment and the fourth embodiment. The photo amplifying apparatus shown in FIG. 16 is different from the photo amplifying apparatus shown in FIG. 15 in that the fixed optical filters 51 and 52 are replaced with variable optical filters 61 and 62, and drive circuits 71 and 72 are added. The drive circuits 71 and 72 control the variable optical filters 61 and 62, respectively, so that the

```
variable optical the wavelength is variable of which the wavelength
                variable optical tilters bl and by transmit!

variable of which the wavelength is variably the variable of which control wait a horording signals of which the control wait a horording signals of which the control wait a horording signals of his transmit!
                                 signals of which the wavelength is variably

the wavelength is variably

the wavelength is variably

is varia
                                                  determined by the control unit 1. Accordingly, the determined the photo amplifying apparatus

determined by 7 of the photo amplifying determine the arbitrarily determine the control unit 16 can arbitrarily determine the control unit 16 can arbitrarily determine the
                                                                         control unit 1 of the photo amplifying apparatus the arbitrarily determine transmit that transmit the the arbitrarily that transmit the arbitrarily that the arbitrarily
                                                                                       shown in FIG. 16 can arbitrarily that transmit the shown in fig. the photo signals and 6?

wavelength ontical filters are avariable ontical filters.
                                                                                                                                                                                                                                                                                                        optical filters bland of rate according apparatus according apparatus according to the photo amplifying apparatus according to the photo amplifying around in the amplifying around in the amplifying according to the photo amplifying apparatus according to the photo amplifying apparatus according to the photo amplifying the photo amplifying the photo according to the
                                                                                                                                             The photo amplifying apparatus according in FIG. 16 operates the photo amplifying in the photo amplify the the sixth the same manner as the photo amplify to the sixth the same manner as the photo amplify to the sixth the same manner as the photo amplify the same manner 
                                                                                                                                                           to the sixth embodiment same manner fifth embodiment shown to the same the fifth embodiment shown as according to the sizably in the same to the fifth embodiment shown in the factor to the fifth embodiment shown in the factor to the fifth embodiment shown in the factor the factor to the factor t
                                                                                                              wavelength optical filters 61 and 62.

Variable optical filters
                                                                                                                                                                                 basically in the same manner as the photo amplifying to the fifth embodiment shown that according to signal of the wavelength the apparatus according to signal of the wavelength apparatus. If the photo signal is.
                                                                                                                                                                                                  apparatus according to signal of the wavelength that and 36 stops due to signal of the wavelength and 36 stops due to signal of the wavelength the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops due to signal of the photo diodes 31 and 36 stops diodes 3
                                                                                                                                                                                                                      FIG. 15. If the photo signal of the wavelength that and 36 stops 1 of the wavelength that 1 of the photo diodes the control unit 1 of example.

15. If the photo signal of the wavelength that and 36 stops 1 of the wavelength that and 36 stops 1 of the wavelength that the photo signal of the wavelength that are the photo signal of the wavelength that the photo signal of the wavelength that are the wavelength that are the wavelength that the wavelength the wavelength that the wavelength the wavelength the wavelength the wavelength the waveleng
                                                                                                                                                                                                                                       is monitored by the photo diodes the control unit 7 of example, according to the to a malfunction, the photo amplifying apparatus to a photo amplifying the photo amplifying to a photo amplifying the photo amplifying the photo amplifying the photo amplifying apparatus according to a photo amplifying the photo amplifying the
                                                                                                                                                                                                                                                           to a mairunction, tor example, the control unit to the apparatus according to the photo amplifying apparatus he nronerly the photo amplifying no longer he nronerly the photo amplifying the photo amplifying no longer he nronerly the photo amplifying to the longer he nronerly to a mairunction, tor example, the nronerly to a mairunction, tor example, the nronerly to the longer he nronerly to a mairunction, tor example, the nronerly to a mairunction, the nronerly the nroner
                               5
                                                                                                                                                                                                                                                                              the photo amplitying apparatus according to properly the photo amplitying apparatus be properly fifth embodiment can no amplitying apparatus according to
                                                                                                                                                                                                                                                                                                             controlled by the photo unit 1 of the emhodiment can to the sixth emhodiment according to the same according to the same according to the apparatus
                                                                                                                                                                                                                                                                                            fifth embodiment can no longer be properly

the photo amplifying apparatus.

controlled by the photo noit 7 of the opening among the photo amplifying apparatus.
                                                                                                                                                                                                                                                                                                                                 However, the control to the photo amplitying apparation apparatus according to the photo amplifying apparatus apparatus according to the photo amplifying apparatus apparatus according to the photo amplifying apparatus apparatus according to the photo amplifying apparatus according to the photo according to the photo amplifying apparatus according to the photo according to the photo
                                                                                                                                                                                                                                                                                                                                                  apparatus according to the photo amplifying apparatus switching the photo amplifying switching the photo amplifying switching the photo amplifying the photo amplifying the switching the photo amplifying the sixth embodiment by switching continuously the sixth embodiment according to
                                                                                                                                                                                                                                                                                                                                                                      continuously control the photo amplifying apparatus the photo amplifying apparatus the photo amplifying the sixth embodiment wavelength.

continuously the sixth to another wavelength the according to the continuous to the 
                                                                                                        20
                                                                                                                                                                                                                                                                                                                                                                                       according to the sixth embodiment by switching to the sixth to another wavelength.

according to the rontrol wait loss continued the rontrol wait loss continued to the sixth embodiment by switching to the sixth embodiment wavelength.
                                                                                                                                                                                                                                                                                                                                                                                                        monitored wavelength to another wavelength. to
monitored wavelength to whit 7 can continue annarative
another wavelength to another amnifiving annarative
another wavelength. to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another wavelength.
to
another can continue
the control whit is another amnifered.
the control wavelength.
the control wavelength.
the control wavelength.
the property control the control wavelength.
the control
                                                                                                                                                                                                                                                                                                                                                                                                                      Accordingly, the control unit 7 can continue to unit 7 can continue to the photo amplifying apparatus.

Accordingly, the the photo amove. according to the properly As described above.
                                                                                                                                                                                                                                                                                                                                                                                                                                                             As described above amplifying apparatus amplifying apparatus to the photo amplifying apparatus amplifying apparatus amplifying apparatus by detecting. The photo amplifying hased for the photo amplifying apparatus amplifying apparatus amplifying apparatus.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 present invention, the photo amplifying apparatus on the photo amplifying apparatus on by detecting, number the number changes in the number controls output signal signals.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  controls output signal level by detecting, based on level by detecting, based on number in the number changes in the photo signals, changes the photo signals, of the photo dain gradient of the change in photo aain gradient of the change and dain gradient of wavelengths
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   the change in photo signals, changes the photo of the photo of wavelengths and gain gradient of wavelengths
                                                                                                                                                                                                                                                                                       20
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      The Present invention is not limited to
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        The present invention is not limited to and modifications and modifications and modifications the score of the variations the score of the these embodiments, departing from the made without departing from the made without departing from the score of the made without departing from the score of the score
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         these embodiments, but variations and modifications the scope of the without departing from the scope without departing from the scope of the may be made without departing from the scope of the scope of the present invention.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               This patent application is based on 2002-264261

This patent application No. contents of the entire contents of the entire priority patent 10. 2002. The entire contents of the filed on september 10.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   Japanese Priority Patent application No. contents of the entire
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  signals.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                present invention.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           30
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   35
```

which are hereby incorporated by reference.